

MV810-Canopen	4	TxPDO	4	RxPDO	PDO	4	16 bit
PDO					" MV800_Canopen.eds "		
RxPDO							

I					
6040h/0		Bit0:	0	1	
		Bit1:	0	1	
		Bit2:	0	1	
		Bit3:	0	1	
		Bit4:	0	1	
		Bit5:	0	1	
		Bit6:	0	1	
		Bit7:	0	1	
2100h/0		:0.1%	0.0	300.0%	0 3000
2101h/0		:0.1%	0.0	300.0%	
2102h/0		:0.01Hz	0.00	599.00Hz	0 59900
2103h/0		:0.01Hz	0.00	599.00Hz	
2104h/0	VF	:1V	0	1000V	
2105h/0	D0	Bit0 D01	0	1	
		Bit1 D02	0	1	
		Bit2 D03	0	1	
		Bit3 R0	0	1	
2106h/0	A01	0.01%	0.00	100.00%	0 10000
2107h/0	HD01	:0.001kHz	0.000	50.000kHz	0 50000
2108h/0	HD02	:0.001kHz	0.000	50.000kHz	
2109h/0	PID	:0.1%	-100.0	100.0%	
210Ah/0	PID	:0.1%	(	-1000 1000)	
210Bh/0			-100.0	100.0%	
210Ch/0					
210Dh/0		:0.1%	-300.0	300.0%	
2100h/0		:0.01Hz	0.00	599.00Hz	

TxPDO	/
-------	---

				Bit0:	0	1		
				Bit1:	0	1		
				Bit2:	0	1		
				Bit3:	0	1		
				Bit4:	0	1		
6041h/0				Bit5:	0	1		
				Bit6:	0	1	1	2
				Bit7:	0	1	1	
				Bit8:	0	1	1	
				Bit9	0	1	2	
				Bit10:	0	1	2	
2200h/0				:0.1A	0.0	6553.5A	0	65535
2201h/0				:1V		0	65535V	
2202h/0				:0.01Hz	0.00	599.00Hz	0	59900
2203h/0				:0.1%		-300.0	300.0%	
2204h/0						-3000	3000	
				:0.1V	0.0	6553.5V		
				Bit0	D11	0	1	
2205h/0				DI	1	0	1	
				Bit1	DI2	0	1	
				Bit2	DI3	0	1	
				Bit3	DI4	0	1	
				Bit0	DI5	0	1	
2206h/0				DI	2	0	1	
				Bit1	DI6	0	1	
				Bit2	DI7	0	1	
				Bit3	DI8	0	1	
				Bit0	DO1	0	1	
2207h/0				DO		0	1	
				Bit1	DO2	0	1	
				Bit2	DO3	0	1	
				Bit3	RO	0	1	
2208h/0								